



PCT

特許協力条約に基づいて公開された国際出願

(51) 国際特許分類6 H04J 13/00, H04B 1/707, H04L 7/00		A1	(11) 国際公開番号 WO96/21294
			(43) 国際公開日 1996年7月11日(11.07.96)
(21) 国際出願番号 PCT/JP96/00006 (22) 国際出願日 1996年1月5日(05.01.96) (30) 優先権データ 特願平7/378 1995年1月5日(05.01.95) JP 特願平7/7205 1995年1月20日(20.01.95) JP (71) 出願人 (米国を除くすべての指定国について) エヌ・ティ・ティ移動通信網株式会社 (NTT MOBILE COMMUNICATIONS NETWORK INC.)[JP/JP] 〒105 東京都港区虎ノ門二丁目10番1号 Tokyo, (JP) (72) 発明者: および (75) 発明者/出願人 (米国についてのみ) 佐和橋衛(SAWAHASHI, Mamoru)[JP/JP] 〒239 神奈川県横須賀市浦賀町5-42-188 Kanagawa, (JP) 安達文幸(ADACHI, Fumiyuki)[JP/JP] 〒236 神奈川県横浜市金沢区高舟台2-35-13 Kanagawa, (JP) (74) 代理人 弁理士 谷 義一(TANI, Yoshikazu) 〒107 東京都港区赤坂5-1-31 第6セイコービル3階 Tokyo, (JP)			(81) 指定国 JP, US, 欧州特許(DE, GB, SE). 添付公開書類 国際調査報告書

(54) Title : DEVICE AND METHOD FOR COHERENT-TRACKING OF CDMA RECEIVER

(54) 発明の名称 CDMA受信機のコヒーレントトラッキング装置および方法

103, 104, 203, 204 ... integrating and dumping
circuit

105 ... automatic frequency controlling circuit

300 ... spreading code replica generator


```

110 ... information symbol delaying section
120 ... pilot symbol phase error
      extracting/averaging section
130 ... information symbol phase error estimating
      section
132 ... information symbol phase compensating
      section
140 ... data identifying section
150 ... judgment code correcting section
220 ... delay circuit
260 ... loop filter
280 ... voltage-controlled clock generator (VCCG)

```

(57) Abstract

A coherent-tracking device of a CDMA receiver, which performs coherent tracking with high accuracy and with low noise. The tracking device is provided with a demodulation coherent detector which performs coherent detection by multiplying a received spread-spectrum signal by a demodulated spreading code replica whose phase is synchronized with the received spreading code contained in the received spread-spectrum signal, an absolute synchronous detector which performs absolute synchronous detection of the coherent signal (compressed-back signals) from the demodulation coherent detector and demodulates information data, a tracking coherent detector which performs coherent detection by multiplying the received spread-spectrum signal by a pair of tracking spread-spectrum code replicas having phases shifted from the phase of the demodulated spreading code replica by $\pm 1/2$ -chip period, a judgement code correcting circuit which reversely modulates the output difference (phase error signal) of the tracking coherent detector with the output of the absolute synchronous detector to remove the information data modulated components contained in the error signal, and a spreading code replica generator which generates a demodulated spreading code replica and a tracking spreading code replica correcting circuit.



BEST AVAILABLE COPY